Figure 6 C1 Q factor and eye diagram distortion dependence on crosstalk. [Color figure can be viewed in the online issue, which is available at www.interscience.wiley.com]

copy, the Q factor of its eye diagram dropped dramatically, which was about 6.8 for 10/20 Gb/s operation, and about 2.8 for 40 Gb/s operation. The eye diagram insets of crosstalk-influenced channels in Figure 6 also indicated that the Q degradation was mainly caused by another signal with the same data on the wavelength of the desired copy, but with different amplitude.

In conclusion, MWC at 10 Gb/s performed the best among the three, but with only about 0.5 higher Q value than the MWC at 20 Gb/s when there was no crosstalk. In the 40 Gb/s case, the average Q factor of the converted signal was above 6.1 without interference. The big performance difference between the 40 Gb/s MWC and the 10/20 Gb/s ones was mainly because, at 40 Gb/s, the operation speed of the MZI modulator at the input was pushed to its limit.

5. CONCLUSIONS

In the letter, we propose a novel MWC scheme for optical multicast by FWM in nonlinear fiber. The MWC apparatus we employed is simple. The approach offers not only strict conversion transparency, but also signal regeneration in the converted channels due to the noise compression effect on the spaces. These advantages are supported by both theoretical analysis and experimental demonstration.

In reality, operating bit rates can often be limited by other components in the setup, as the case shown in our 40 Gb/s experiments. Eliminating such limitations is the key to improve experimental performance at high bit rates. Further, increasing the nonlinearity of the WC media can also improve the conversion efficiency and enlarge the useable wavelength span.

ACKNOWLEDGMENTS

The authors thank the NoE e-Photon/One+ project and the IST-LASAGNE project for funding these research activities and SIE-MENS SA for providing their lab facilities for this work.

REFERENCES

1. G. Contestabile, M. Presi, and E. Ciaramella, Multiple wavelength conversion for WDM multicasting by FWM in an SOA, *IEEE Photon Technol Lett* 16 (2004), 1775–1777.
2. Y. Shen, J.H. Ng, C. Lu, T.H. Cheng, and M.K. Rao, Single to multi wavelength conversion using amplified spontaneous emission of semi-

- conductor optical amplifier. In: Paper presented at the Optical Fiber Communication Conference, OFC'01, 2001, pp. ME1–1–ME1–13.
3. S. Watanabe, S. Takeda, G. Ishikawa, H. Ooi, J.G. Nielsen, and C. Sonne, Simultaneous wavelength conversion and optical phase conjugation of 200 Gb/s (5×40 Gb/s) WDM signal using a highly nonlinear fiber four-wave mixer. In: Proceedings of the 23rd European Conference on Optical Communication, ECOC'97, 2001, pp. 1–4.
4. H.S. Chung, R. Inohara, K. Nishimura, and M. Usami, All-optical multi-wavelength conversion of 10 Gbit/s NRZ/RZ signals based on SOA-MZI for WDM multicasting. *Electron Lett* 41 (2005).
5. K.K. Chow and C. Shu, All-optical signal regeneration with wavelength multicasting at 6×10 Gb/s using a single electroabsorption modulator. *Opt Express* 12 (2004), 3050–3054.
6. C.W. Chow, C.S. Wong, and H.K. Tsang, All-optical modulation format conversion and multicasting using injection-locked laser diodes. *IEEE J Lightwave Technol* 22 (2004), 2386–2392.
7. G. Kalogerakis, M.E. Marhic, and L.G. Kazovsky, Multiple-wavelength conversion with gain by a high-repetition-rate pulsed-pump fiber OPA. *IEEE J Lightwave Technol* 23 (2005), 2954–2960.
8. S.J.B. Yoo, Wavelength conversion technologies for WDM network applications. *J Lightwave Technol* 14 (1996), 955–966.
9. E. Ciaramella, F. Curti, and S. Trillo, All-optical signal reshaping by means of four-wave mixing in optical fibers, *IEEE Photon Technol Lett* 13 (2001), 142–144.
10. D.M. Forin, F. Curti, G.M. Tosi Belleffi, and F. Matera, All optical fibre 2 + 1 auxiliary carrier transponder-regenerator. *IEEE Photon Technol Lett* 17 (2005).
11. R. Thompson and R. Roy, Nonlinear dynamics of multiple four-wave mixing processes in a single-mode fiber. *Phys Rev A* 43 (1991), 4987–4996.
12. R. Thompson and R. Roy, Statistical fluctuations in multiple four-wave mixing in a single-mode optical fiber. *Phys Rev A* 44 (1991), 7605–7614.

© 2007 Wiley Periodicals, Inc.

FLEXIBLE-SUBSTRATE LOW-COST CONSTRUCTION OF A COPLANAR-WAVEGUIDE APERTURE-COUPLED MICROSTRIP PATCH ANTENNA

Dominic Depret,¹ Hendrik Rogier,¹ Kristof Dhaenens,² and Jan Vanfleteren²

¹ Department of Information Technology, Ghent University, Sint-Pietersnieuwstraat 41, 9000 GENT, Belgium

² Department of Electronics and Information Systems, Ghent University, Sint-Pietersnieuwstraat 41, 9000 GENT, Belgium

Received 26 September 2006

ABSTRACT: An innovative and cost-effective procedure for building multi-layered planar antennas is presented. The antenna is constructed by defining copper patterns forming the feed plane and the antenna plane on a single flexible polyimide substrate and by folding the flex around a low ϵ_r and low-loss spacer. By a suitable choice of transfer tape to assemble the different layers, a high alignment accuracy and low substrate losses are ensured. To illustrate our new approach, the design and manufacturing of a coplanar-waveguide aperture-coupled patch antenna covering the complete 2.45 GHz ISM band is described. By means of reflection and transmission measurements, the high gain and high efficiency of the antenna prototypes are demonstrated. © 2007 Wiley Periodicals, Inc. *Microwave Opt Technol Lett* 49: 1071–1074, 2007; Published online in Wiley InterScience (www.interscience.wiley.com). DOI 10.1002/mop.22355

Key words: planar antennas; flexible substrates; wireless local area networks

1. INTRODUCTION

In recent years, applications using wireless local area networks (WLANs) have expanded rapidly. Several wireless communications protocols, for example, Zigbee (IEEE 802.15.4), Bluetooth [1] (IEEE 802.15), WiFi (IEEE 802.11 b/g), Wireless USB, and WiMAX (IEEE 802.16a), are operating in unlicensed frequency bands, such as the 2.45 GHz Industrial Scientific Medical (ISM) band (2.4–2.4835 GHz). Planar inverted-F antennas, monopoles, and patch antennas on printed circuit boards are frequently used in wireless applications. However, monopoles have protruding parts, leading to vulnerability and a nonplanar construction. Planar inverted-F antennas, punched out of metal, also are vulnerable and usually quite thick (typically around 10 mm). Patches placed on a printed circuit board often require vias. They are rigid and very expensive in a multilayer construction. In literature, several new flexible materials, such as foams [1] and textile garments [2], have been proposed to serve as antenna substrate. Very thin flexible films such as polyimide have also been applied in flexible antenna design. The antenna topologies consist of a single layer of polyimide flex substrate on which a printed monopole [3] or planar inverted-F antenna [4] were defined. Since the antenna is nonplanar and protruding, it is quite vulnerable and its characteristics are quite sensitive to objects placed in its near-field environment. In this article, we present an innovative construction process for a multi-layered antenna topology defined on a single flexible substrate. As described in Section 2, the antenna layers, the ground planes and the feed planes are constructed by folding a single very flexible substrate, on which the different conductor patterns are defined, around spacers. Vias and protruding parts are avoided, and a low ϵ_r and low-loss spacer is applied for robustness. The technique is applied in Section 3 to construct a coplanar-waveguide aperture-coupled microstrip patch antenna consisting of a feed plane and an antenna plane. The antenna covers the complete 2.45 GHz ISM band, exhibits low losses and provides a high antenna gain.

Figure 1 Geometry of the coplanar-waveguide aperture-coupled patch antenna

TABLE 1 Dimensions of the coplanar-waveguide aperture-coupled patch antenna

patch		Feed section	
L_p [mm]	46	L_a [mm]	34.94
W_p [mm]	40	W_a [mm]	2.38
(x_{pos}, y_{pos}) [mm]	(19; 0)	L_{stub} [mm]	7.60
Coplanar waveguide		$L_{stubfree}$ [mm]	0.3
W_{cpw1} [mm]	4.93	L_{gr} [mm]	75
W_{cpw2} [mm]	0.09	W_{gr} [mm]	60

2. ANTENNA CONSTRUCTION PROCESS

The cost-effective construction is obtained by defining copper patterns forming the feed plane and the antenna plane on a single flexible substrate and by folding the flex around the spacer. The flex substrate, on which the conducting parts of the antenna are defined by means of a standard lithography process, consists of a single copper layer placed on a 25- μm thick polyimide film with relative permittivity $\epsilon_r = 2.5$. The film offers substantial flexibility as it allows bending around sharp corners. As spacer we applied the low-cost Emerson & Cuming Eccostock SH material [5], consisting of a 5-mm thick polyurethane foam layer with well-defined uniform permittivity of $\epsilon_r = 1.08$ and low losses ($\tan \delta = 0.002$). Although this spacer is quite rigid, the design and construction procedure could easily be extended to more flexible spacers, resulting in fully flexible antennas. Finally, both flex and spacer are connected by Nitto Denko D5952 transfer tape [6]. This 80- μm -thick nonconducting tape is specifically suited for glueing polyurethane surfaces and it can also be used on copper and polyimide. By using an adhesive tape instead of liquid glue, a very fast and accurate assembly of the different layers is possible, thanks to small alignment marks which were added to the design. Since this tape is relatively thin, its effects on the antenna performance are very limited. As permittivity and loss tangent of the tape were not specified, simulations are based on the assumption of $\epsilon_r = 2.5$ and $\tan \delta = 0.002$.

3. SIMULATION AND MEASUREMENT RESULTS

Aperture-coupled microstrip patch antennas allow designing broadband planar antennas without the need of vias between different layers. A coplanar-waveguide aperture-coupled patch antenna [7–9] can be implemented on a single spacer since only two layers of copper are required, that is, a feed plane and an antenna plane. The topology shown in Figure 1 was simulated and optimized using the field simulator Advanced Design System (ADS) Momentum from Agilent Technologies, resulting in the optimized dimensions specified in Table 1. The simulations are

Figure 2 Construction of prototype 1 (bottom view). [Color figure can be viewed in the online issue, which is available at www.interscience.wiley.com]

Figure 3 Construction of prototype 1 (top view). [Color figure can be viewed in the online issue, which is available at www.interscience.wiley.com]

based on the assumption of an infinite ground plane. The actual values L_{gr} and W_{gr} of the ground plane in Table 1 are derived from measurements, by a stepwise reduction of the size of the ground plane (starting from 100 mm $\times$ 100 mm), such that the performance of the antenna remains almost unchanged. Note that the impedance bandwidth was increased by moving the aperture along the X-direction. Compared to an aperture located at the center of the patch, this leads to smaller coupling between feed and patch, but by enlarging the aperture dimensions, coupling is increased to the desired level. In Figure 2 the feed plane of prototype 1 is shown and in Figure 3 the antenna plane of prototype 1 is presented. Figure 4 demonstrates that the simulated design yields a bandwidth of 211 MHz, that is, $S_{11} < -10$ dB for 2.370–2.581 GHz. The simulated bandwidth is more than sufficient to cover to complete ISM band. In fact, we designed for a larger bandwidth in order to obtain a high production yield by making the antenna robust against small shifts in resonance frequency or matching conditions, due to alignment errors, tolerances on the antennas dimensions or bending of the substrate, or uncertainties about the permittivity and loss tangent of the different materials. Indeed, because of the unknown characteristics of the transfer tape, the frequency bands of the two prototypes are lower in frequency than simulations indicate: 2296–2540 MHz and 2248–2503 MHz, resulting in a bandwidth of 244 MHz and 255 MHz, respectively. Both prototypes differ in the way the flex was oriented on the spacer. One prototype is glued with the polyimide side on the spacer (prototype 1, Figs. 2 and 3) and the other with the copper side towards the

Figure 4 Measured and simulated return loss (S_{11})

Figure 5 Measured antenna directivity in XZ-plane

spacer (prototype 2). The effect on the antenna characteristics is found to be marginal. The antenna directivity measured at 2.4 GHz along the XZ-plane is shown in Figure 5 whereas the directivity measured along the YZ-plane is depicted in Figure 6. Note that the antenna has a dominant linear polarization and that the back radiation remains more than 12 dB below the main beam level. The antenna gain along the broadside (z-axis) direction is plotted in Figure 7. One observes that the antenna gain remains above 8.5 dBi in the complete ISM band.

Figure 6 Measured antenna directivity in YZ-plane

Figure 7 Measured antenna gain along broadside

4. CONCLUSIONS

A new construction technique for multilayered planar antennas was presented. All conducting patterns defining the antenna and feed sections were defined on a single very thin flexible polyimide substrate, which was then folded around a spacer. A transfer tape was used to connect the polyimide substrate to the spacer. A robust coplanar-waveguide aperture-coupled antenna was successfully manufactured, offering sufficient bandwidth to cover the entire 2.45 GHz ISM band. Moreover, low back radiation levels and a high antenna gain were measured, proving that substrate and conductive losses were sufficiently low to obtain high antenna efficiency. A small shift towards lower frequencies was observed when applying the transfer tape.

ACKNOWLEDGMENT

H. Rogier is a postdoctoral researcher of the FWO-V. His research was supported by a grant of the DWTC/SSTC, MOTION project.

REFERENCES

1. C. Cibi, P. Leuchtman, M. Gimersky, R. Vahldieck, and S. Mosciro, A flexible wearable antenna, *Proc IEEE Int Symp Antennas Propagation* 4 (2004), 3589–3592.
2. A. Tronquo, H. Rogier, C. Hertleer, and L. Van Langenhove, A robust planar textile antenna for wireless body LANs operating in the 2.45-GHz ISM band, *IEE Electronics Lett* 42 (2006), 142–143.
3. W.-C. Liu and C.-F. Hsu, Flexible CPW-fed double meandered monopole antenna for dual-band WLAN operation, *Microwave Opt Technol Lett* 48 (2006), 1529–1532.
4. P. Salonen, M. Keskilampi, J. Rantanen, and L. Sydänheimo, A novel Bluetooth antenna on flexible substrate for smart clothing, *IEEE Int Conf Systems Man Cybernetics* 2 (2001), 789–794.
5. <http://www.eccosorb.com/catalog/eccostock/sh.pdf>.
6. N. Denko, <http://www.nittoeurope.com>.
7. R.Q. Lee and R.N. Simons, Coplanar-waveguide aperture-coupled microstrip patch antenna, *IEEE Microwave Guided Wave Lett* 2 (1992), 138–139.
8. L. Giauffret, J.M. Laheurte, and A. Papiernik, Experimental and theoretical investigations of new compact large bandwidth aperture coupled microstrip antenna, *Electronics Lett* 31 (1995), 2139–2140.
9. L. Giauffret, J.M. Laheurte, and A. Papiernik, Study of various shapes of the coupling slot in CPW-fed microstrip antennas, *IEEE Trans Antennas Propagation* 45 (1997), 642–647.

FULLY EMBEDDED HIGH Q CIRCULAR STACKED SPIRAL INDUCTORS INTO ORGANIC SUBSTRATE

Hwan H. Lee and Jae Y. Park

Department of Electronic Engineering, Kwangju University, 447-1 Wolgye-Dong, Nowon-Gu, Seoul 139-701, Korea

Received 26 September 2006

ABSTRACT: In this paper, fully embedded circular-stacked spiral inductors are investigated into a multilayered PCB substrate for low cost and miniaturized RF system on package (SOP) applications. The embedded circular-stacked inductors are optimally designed to obtain high quality factor and self-resonant frequency by using 3D EM simulator. The fabricated two-turn circular-stacked inductor has an inductance of 8.4 nH and a maximum quality factor of 67 at 1.2 GHz. The device size of the stacked inductor is ~65% of the planar inductor. The measured performance characteristics are well matched with the 3D EM-simulated ones. The embedded circular stacked spiral inductors are promising for organic-based SOP, which needs various functionality, low cost, small size and volume, and high packaging density. © 2007 Wiley Periodicals, Inc. *Microwave Opt Technol Lett* 49: 1074–1077, 2007; Published online in Wiley InterScience (www.interscience.wiley.com). DOI 10.1002/mop.22354

Key words: embedded; circular stacked; spiral inductor; quality factor; organic SOP; PCB

1. INTRODUCTION

As a large number of passive components are demanded to realize advanced information and communication systems, embedded or integrated passive components are being investigated with high performance characteristics, low cost, small size and volume, and high density. Integration or embedding of the passive components can result in reducing assembly costs, improving electrical performance and packaging efficiency, mass production by batch fabrication, low volume and light weight, etc. In particular, the embedded passives are crucial role to realize a system on package (SOP) that is considered as one of the most challenged and exciting research area for realizing the advanced electronic systems [1]. Among these passive components, inductor is the most studied one to overcome some drawbacks such as complexity of fabrication, low quality factor, and high cost, since it is the core component in affecting the performance of RF/microwave circuits such as voltage-controlled oscillators, filters, high-impedance RF chokes, and impedance-matching networks. Much research has been done to realize embedded inductors based on low temperature co-fired ceramics [2, 3]. However, the ceramic will shrink depending on the materials during the firing process, which will lead to the limitation of the product reliability and the component yield. Several studies about the embedded inductors on FR-4 substrate have been performed for RF and microwave SOP applications [4, 5]. But these planar inductors are limited to use in realizing the miniaturized, embedded passive circuits and SOP, since they occupy large component area.

In this paper, fully embedded circular-stacked spiral inductors are proposed into the printed circuit board (PCB) for small size and low cost RF SOP applications. The circular-stacked spiral inductors are fully embedded into a multilayered PCB to reduce their size, and optimally designed by using 3D EM simulator to achieve high-quality factors.