Padé Approximate Solution for Wave Propagation in Graded-Index Metamaterials

Khai Q. Le^{*} and Peter Bienstman

*Photonics Research Group, Department of Information Technology, Ghent University-IMEC,
Sint-Pietersnieuwstraat 4, B-9000 Ghent, Belgium*

^{}Corresponding author: khai.le@intec.ugent.be*

A new approximate solution for wave propagation in graded-index media is developed whereby the exact wave propagation equation is replaced by any one of a sequence of higher-order (m,n) Padé approximant operators. The resulting formulations may be discretized by common numerical schemes and solvable by existing numerical techniques. The accuracy of this approximate calculation of the wave propagator is demonstrated in comparison with the exact result. We then employ the resulting method to investigate wave propagation in metamaterials with graded-index profiles changing according to a hyperbolic tangent function along the propagation direction.

Keywords: *Padé approximant operators, wave propagation, graded-index metamaterials*

1. Introduction

Electromagnetic (EM) metamaterials, a new class of artificial composite materials, have recently attracted intensive interests due to their potential for new applications such as negative refraction, inverse Doppler effect, and radiation tension instead of pressure [1,2], as well as electromagnetic cloaking of arbitrary shaped objects [3]. In addition, there has been a growing

research interest in the propagation behavior of EM waves in metamaterials with material properties changing during propagation direction.

There exist analytical and numerical approaches to investigate wave propagation in optical structures incorporating metamaterials with graded-index profiles such as the invariant embedding method [4] and the finite difference time domain (FDTD) method [5,6]. While the analytical methods are currently limited to low-dimensionality problems, the FDTD method is well-known as a time-consuming method, especially for three dimensional structures. Efforts to find more efficient methods for large computational problems are thus very imperative. In this paper, we present a new approximate solution for wave propagation whereby the exact wave propagation operator is approximated by any one of a sequence of higher-order (m,n) Padé approximant operators. The resulting formalism offers a substantial advantage in terms of an accurate and efficient solution of high-dimensionality wave propagation problems.

2. Formulation

For isotropic metamaterials we assume that their optical properties can be described by the effective dielectric permittivity and the effective magnetic permeability. Furthermore, with EM fields that are periodic in time according to a $\exp(-i\omega t)$ dependency we can obtain the scalar wave equations for the electric field (E_y) and the magnetic field (H_x) components from Maxwell's equations as follows [7]:

$$\frac{\partial^2 E_y}{\partial z^2} + \frac{\partial^2 E_y}{\partial x^2} + \frac{\partial^2 E_y}{\partial y^2} - \frac{1}{\mu} \frac{\partial \mu}{\partial z} \frac{\partial E_y}{\partial z} + \omega^2 \mu \epsilon E_y = 0 \quad (1)$$

or

$$\frac{\partial^2 H_x}{\partial z^2} + \frac{\partial^2 H_x}{\partial x^2} + \frac{\partial^2 H_x}{\partial y^2} - \frac{1}{\epsilon} \frac{\partial \epsilon}{\partial z} \frac{\partial H_x}{\partial z} + \omega^2 \mu \epsilon H_x = 0 \quad (2)$$

where $\epsilon=\epsilon(\omega,z)$ and $\mu=\mu(\omega,z)$ are the frequency-dependent electric permittivity and magnetic permeability, respectively. These equations describe the propagation of EM waves through a medium of which the constitutive parameters vary along the propagation direction z-axis.

We now start to solve these equations numerically and investigate the propagation of EM waves through a graded-index metamaterial structure. The transition between negative and positive index media was ignored in this paper. We choose a graded-index profile for both the permittivity and the permeability to make sure that their first derivative terms are non-zero. For simplification purposes, we only consider Eq. (1) as those for Eq. (2) are equivalent. Eq. (1) can be rewritten as:

$$Q \frac{\partial E_y}{\partial z} - \frac{\partial^2 E_y}{\partial z^2} = P E_y \quad (3)$$

where $P = \nabla_{\perp}^2 + \omega^2 \mu \epsilon = \frac{\partial^2}{\partial x^2} + \frac{\partial^2}{\partial y^2} + \omega^2 \mu \epsilon$ and $Q = \frac{1}{\mu} \frac{\partial \mu}{\partial z}$.

We may formally rewrite Eq. (3) in the form

$$\frac{\partial E_y}{\partial z} = \frac{P}{Q - \frac{\partial}{\partial z}} E_y \quad (4)$$

Equation (4) suggests the following recurrence relation

$$\left. \frac{\partial}{\partial z} \right|_{n+1} = \frac{P}{Q - \left. \frac{\partial}{\partial z} \right|_n} \quad (5)$$

This recurrence relation is the well-known form in the area of guided-wave optics which results in either the real or the modified Padé approximant operators depending on its initial value [9-11]. If Eq. (5) is used to replace the first derivative of fields with respect to z with an expression containing only the operator P, then a propagator of the following form is obtained:

$$\frac{\partial E_y}{\partial z} \approx \frac{N}{D} E_y. \quad (6)$$

where N and D are polynomials in P .

2.1 Real Padé Approximant Operators

In case the initial value of $\left. \frac{\partial}{\partial z} \right|_0 = 0$ is used, this gives us a real Padé(m,n) approximant-based wave

propagation formula as follows:

$$\frac{\partial E_y}{\partial z} \approx Q \frac{A(m)}{B(n)} E_y \quad (7)$$

where $A(m)$ and $B(n)$ are polynomials in $X = \frac{P}{Q^2}$. The most useful low-order Padé(m,n)

approximant operators are shown in Table 1.

If Eq. (7) is compared with a formal solution of Eq. (1) written in the well-known form

$$\frac{\partial E_y}{\partial z} = Q \left(\frac{1}{2} - \sqrt{\frac{1}{4} - X} \right) E_y, \quad (8)$$

we obtain the approximation formula

$$\frac{1}{2} - \sqrt{\frac{1}{4} - X} \approx \frac{A(m)}{B(n)}. \quad (9)$$

Since the operator X has a real spectrum, it is useful to consider the approximation of $\frac{1}{2} - \sqrt{\frac{1}{4} - X}$

by the Padé approximant operators. Fig. 1 shows the absolute values of $\frac{1}{2} - \sqrt{\frac{1}{4} - X}$ and the most

useful low-order Padé(m,n) approximant operators with respect to X . It is shown that the real approximations Padé(m,n) are a good fit to the exact solution of the wave equation. Furthermore, it is clearly seen that the higher order of the approximation Padé(m,n) is, the more accurate approximation to wave propagator is obtained. However, if the denominator of the real

approximation Padé(m,n) formula approaches zero, its absolute value approaches ∞ as clearly seen in Fig. 2. Physically, the real Padé approximant operators incorrectly propagate evanescent modes. To circumvent this problem, we introduce modified Padé approximant operators as follows:

2.2 Modified Padé Approximant Operators

By sharing the same idea with the real Padé approximant operators but using a different initial value we obtain the modified Padé approximant operators. Here, we derive this initial value for the specific problem that we are considering here.

From Eq. (4) we can derive the relevant form as follows:

$$-\frac{2}{Q} \frac{\partial}{\partial z} = \frac{-\frac{4P}{Q^2}}{2 - \frac{2}{Q} \frac{\partial}{\partial z}}. \quad (10)$$

This equation may be rewritten by

$$f(Y) = \frac{Y}{2 + f(Y)} \quad (11)$$

where $f(Y) = -\frac{2}{Q} \frac{\partial}{\partial z}$ and $Y = -\frac{4P}{Q^2}$

Eq. (11) suggests the recurrence relation

$$f_{n+1}(Y) = \frac{Y}{2 + f_n(Y)} \text{ for } n=0,1,2,\dots \quad (12)$$

Y. Y. Lu [12] has proved that Eq. (12) can provide a good approximation to $\sqrt{1+Y} - 1$ with the initial value of

$$f_o(Y) = i\beta \text{ where } \beta > 0 \text{ is a damping parameter.} \quad (13)$$

Subsequently, our modified Padé approximant operators are obtained from the same recurrence

formula (5) with a different initial value of $\frac{\partial}{\partial z}\bigg|_0 = -i\frac{\beta}{2}Q$. The most useful low-order modified

Padé approximant operators are also shown in Table 1.

The absolute value and real part of the modified Padé(1,1) approximant of $\frac{1}{2} - \sqrt{\frac{1}{4} - X}$ are also depicted in Fig. 2. It is seen that the modified Padé(1,1) (with $\beta=2$) allows more accurate approximation to the true wave equation than the real Padé(1,1) operator. Furthermore, the real one incorrectly propagates evanescent modes as its denominator gradually approaches zero. In contrast, the modified Padé operator could give waves propagating in evanescent regions the desired damping as shown in the same figure.

2.3 Numerical implementation of Padé-based wave propagation

One of the most commonly used techniques to numerical deal with Eq. (7) is the finite difference method. Finite difference equations may be derived from Eq. (7) by clearing the denominator and centering with respect to z in the usual way:

$$B(E_y^{n+1} - E_y^n) = \frac{Q^n \Delta z}{2} A(E_y^{n+1} + E_y^n). \quad (14)$$

Eq. (14) can be solved effectively by a multistep method whereby each component step is treated by the traditional direct matrix inversion (DMI) [11]. However, for large problems requiring huge memory to establish matrix inversion DMI is very slow. For the last decade alternative methods have been proposed to solve matrix inversion effectively by iteration techniques such as Bi-CGSTAB [13]. However, for large three-dimensional problems where the material properties change frequently and which therefore require frequent matrix inversions, this can still be a

numerically intensive task. Recently, we reported a different approach by using the new complex Jacobi iterative (CJI) method [14]. There, the wave propagation equation is recast in terms of a Helmholtz equation with a source term. The utility of the CJI technique depends mostly upon its execution speed dominated by the amount of effective absorption (or medium loss). If the medium loss is high, the convergence rate is thus fast.

3. Example

In order to prove the applicability of this approximant method, we now employ it to study wave propagation in an inhomogeneous negative index metamaterial whereby the effective permittivity and permeability vary according to a hyperbolic tangent function. Of course, our method works equally well for positive-index graded materials.

We consider an electric wave propagating in a medium where ϵ and μ are both always non-zero and are given by the following functions (see Fig. 3):

$$\epsilon = -\epsilon_0 \epsilon_{\text{eff}}(\omega)(\tanh(\rho z) + 2), \mu = -\mu_0 \mu_{\text{eff}}(\omega)(\tanh(\rho z) + 2). \quad (15)$$

where ρ ($=10^{+6}$) is a positive parameter ensuring index profiles to be graded and the first derivative of ϵ and μ are therefore non-zero. We assume a wave with wavelength of $\lambda_0 = 1 \mu\text{m}$ propagating in such medium of $\epsilon_{\text{eff}}(\lambda_0) = \mu_{\text{eff}}(\lambda_0) = 1$. Figure 4 shows the comparison of the calculated results obtained by the solution from the real Padé operator, the modified Padé operator and the true wave equation (are solved directly by the finite element method in the commercial software-COMSOL multiphysics [15]). It is seen that the result obtained from the modified Padé operator allows a better agreement to the true wave equation than that of the real one.

4. Conclusions

In this paper, we have derived a new approximate solution for wave propagation in graded-index media based on Padé approximant operators. The resulting formulas allow accurate approximations to the true wave equation. It results in a promising tool to investigate wave propagation in media where the permittivity and the permeability changing during propagation direction.

Acknowledgments

Parts of this work were performed within the context of the Belgian IAP project Photonics@Be.

References

1. V. G. Veselago, “The electrodymanics of substances with simultaneously negative value of ϵ and μ ,” Sov. Phys. Ups **10**, 509-514 (1968).
2. R. A. Shelby, D. R. Smith, and S. Schultz, “Experimental verification of a negative index of refraction,” Science **292**, 77-79 (2001).
3. J. B. Pendry, D. Schurig, and D. R. Smith, “Controlling electromagnetic fields,” Science **312**, 1780-1782 (2006).
4. K. Kim, D.-H. Lee, and H. Lim, “Resonant absorption and mode conversion in a transition layer between positive-index and negative-index media,” Opt. Express **16**, 18505-18513 (2008).
5. R. W. Ziolkowski and E. Heyman, “Wave propagation in media having negative permittivity and permeability,” Phys. Rev. E **64**, 056625 (2001).
6. R. W. Ziolkowski, “Pulsed and CW Gaussian beam interaction with double negative metamaterial slabs,” Opt. Express **11**, 662-681 (2003).

7. M. Dalarsson and P. Tassin, "Analytical solution for wave propagation through a graded index interface between a right-handed and a left-handed material," *Opt. Express* **17**, 6747–6751 (2009).
8. G. R. Hadley, "Wide-angle beam propagation using Padé approximant operators," *Opt. Lett.* **17**, 1426-1428 (1992).
9. Khai Q. Le and P. Bienstman, "Wide-angle beam propagation method without using slowly varying envelope approximation," *J. Opt. Soc. Am. B*, **26**, 353-356, (2009).
10. Khai Q. Le, "Complex Padé approximant operators for wide-angle beam propagation," *Opt. Commun.* **282**, 1252-1254 (2009).
11. G. R. Hadley, "Multistep method for wide-angle beam propagation," *Opt. Lett.* **17**, 1743-1745 (1992).
12. Y. Y. Lu, "A complex coefficient rational approximation of $\sqrt{1+x}$," *App. Numer. Math.* **27**, 141 (1998).
13. H. A. Van der Vorst, "Bi-CGSTAB: A fast and smoothly converging variant of Bi-CG for the solution of nonsymmetric linear systems," *SIAM J. Sci. Stat. Comput.* **13**, 631-644 (1992).
14. Khai Q. Le, R. G. Rubio, P. Bienstman, and G. R. Hadley, "The complex Jacobi iterative method for three-dimensional wide-angle beam propagation," *Opt. Express* **16**, 17021-17030 (2008).
15. COMSOL, <http://www.comsol.com>

List of captions:

Table caption:

+ Table 1: Most useful low-order Padé approximants for wave propagator in terms of the

operator $X = \frac{P}{Q^2}$

Figure captions:

+ Fig 1. The absolute values of $f(X) = \frac{1}{2} - \sqrt{\frac{1}{4} - X}$ and the most useful low-order Padé approximant operators.

+ Fig. 2. The absolute values (a) and real part (b) of $f(X) = \frac{1}{2} - \sqrt{\frac{1}{4} - X}$, the most useful low-order real and complex Padé approximant operators.

+ Fig. 3. The permittivity and permeability vary along the propagation direction according to a hyperbolic tangent function assumed in this paper.

+ Fig. 4. Propagation of electric wave in graded-index structure with positive index profile changing according to hyperbolic tangent function.

TABLE 1
MOST USEFUL LOW-ORDER PADÉ APPROXIMANTS FOR WAVE PROPAGATOR IN TERMS OF THE OPERATOR $X = \frac{P}{Q^2}$

Order	Expression	
	Padé	Modified Padé
(1,1)	$\frac{X}{1-X}$	$\frac{X}{1 - \frac{1}{1+i\beta/2}X}$
(2,2)	$\frac{X-2X^2}{1-3X+X^2}$	$\frac{X - \left(1 + \frac{1}{1+i\beta/2}\right)X^2}{1 - \left(2 + \frac{1}{1+i\beta/2}\right)X + \frac{1}{1+i\beta/2}X^2}$
(3,3)	$\frac{X-4X^2+3X^3}{1-5X+6X^2-X^3}$	$\frac{X - \left(3 + \frac{1}{1+i\beta/2}\right)X^2 + \left(1 + \frac{2}{1+i\beta/2}\right)X^3}{1 - \left(4 + \frac{1}{1+i\beta/2}\right)X + \left(3 + \frac{3}{1+i\beta/2}\right)X^2 - \frac{1}{1+i\beta/2}X^3}$

Fig. 1. The absolute values of $f(X) = \frac{1}{2} - \sqrt{\frac{1}{4} - X}$ and the most useful low-order Padé approximant operators.

Fig. 2. The absolute values (a) and real part (b) of $f(X) = \frac{1}{2} - \sqrt{\frac{1}{4} - X}$, the most useful low-order real and complex Padé approximant operators.

Fig. 3. The permittivity and permeability vary along the propagation direction according to a hyperbolic tangent function assumed in this paper.

Fig. 4. Propagation of electric wave in graded-index structure with positive index profile changing according to hyperbolic tangent function.